

# NEPSI Hazardous Area Approvals for Fisher® FIELDVUE™ DVC6200 Series Digital Valve Controllers

This supplement provides NESPI Hazardous Area Approval information for DVC6200 Series digital valve controllers.

NEPSI—National Supervision and Inspection Centre for Explosion Protection and Safety of Instrumentation. NEPSI approval is accepted in China.

These special instructions for “safe use” are in addition to, and may override, the standard installation procedures. Certain nameplates may carry more than one approval, and each approval may have unique installation/wiring requirements and/or conditions of “safe use”. Special instructions are listed by approval.

Refer to the DVC6200 Series quick start guide or the appropriate product instruction manual for all other information pertaining to the DVC6200 Series digital valve controller. If additional information regarding these products is required, contact your [Emerson Process Management sales office](#) or go to [www.FIELDVUE.com](http://www.FIELDVUE.com).



- [DVC6200 Series Digital Valve Controller Quick Start Guide \(D103556X012\)](#)
- [DVC6200 HW2 Digital Valve Controller Instruction Manual \(D103605X012\)](#)
- [DVC6200 HW1 Digital Valve Controller Instruction Manual \(D103409X012\)](#)
- [DVC6200 SIS Digital Valve Controller Instruction Manual \(D103557X012\)](#)
- [DVC6200f Digital Valve Controller Instruction Manual \(D103412X012\)](#)
- DVC6200p Digital Valve Controller Instruction Manual (pending)

---

## Note

This information supplements the nameplate markings affixed to the product.

Always refer to the nameplate itself to identify the appropriate certification.

---

## WARNING

Failure to follow these conditions of “safe use” could result in personal injury or property damage from fire or explosion, and area re-classification.

---



**Intrinsically Safe**

Certificate Number GYJ15.1044X

Ex ia IIC T4/T5/T6 Ga

**Special Conditions for Safe Use**

The suffix “X” placed after the certificate number indicates that this product is subject to special conditions for safe use, that is:

1. For EPL Ga applications, at the metallic parts of the products made of light metal there is a danger of ignition by impact or friction.
2. Avoid of the electrostatic charge built on the surface of non-metallic material of the product.

**Conditions for Safe Use**

1. The external earth connection facility shall be connected reliably.
2. This product should be used in explosive gas atmospheres together with approved associated apparatus, follow the instruction manual of this product and associated apparatus when connecting the wiring. Connect the wiring terminals correctly.
3. The intrinsically safe parameters are shown as follows:

3a. DVC6200, DVC6200S

Ui (V)	Ii (mA)	Pi (W)	Ci (nF)	Li (mH)
30	226	1.4	5	0.55

3b. DVC6200 (HW2), DVC6200S (HW2)

	Ui (V)	Ii (mA)	Pi (W)	Ci (nF)	Li (mH)
Loop Terminals	30	130	1	15	0.55
Output Terminals	28	100	1	15	0.5

3c. DVC6200F, DVC6200FS, DVC6200P, DVC6200PS

Ui (V)	Ii (mA)	Pi (W)	Ci (nF)	Li (mH)
24	380	1.4	5	0
17.5	380	5.32	5	0

3d. DVC6205 (HW2)

	Ui (V)	Ii (mA)	Pi (W)	Ci (nF)	Li (mH)
Loop Terminals	30	130	1	15	0.55
Output Terminals	28	100	1	15	0.5

Output parameters of the remote sensor: Uo = 30V I<sub>o</sub> = 21.2mA Po = 160mW Co = 55nF Lo = 78mH

3e. DVC6205F, DVC6205P

	Ui = 24V	Ii = 380mA	Pi = 1.4W	Ci = 5nF	Li = 0mH
	Uo = 24V	Io = 44mA	Po = 0.33W	Co = 121nF	Lo = 30mH
or	Ui = 17.5V	Ii = 380mA	Pi = 5.32W	Ci = 5nF	Li = 0mH
	Uo = 17.5V	Io = 44mA	Po = 0.33W	Co = 121nF	Lo = 30mH

3f. DVC6215

Ui (V)	Ii (mA)	Pi (W)	Ci (nF)	Li (mH)
30	226	1.4	50	0.55

4. Connecting cable between this product and associated apparatus should be insulated screen cable; connect the cable screen functionally to earth ground.
5. After installation, degree of protection of enclosure is at least IP66 according to GB4208-2008.
6. The user shall not change the configuration in order to maintain/ensure the explosion protection performance of the equipment. Any change may impair safety.
7. For installation, use and maintenance of this product, the end user shall observe the instruction manual and the following standards:
  - GB50257-1996 “Code for construction and acceptance of electric device for explosion atmospheres and fire hazard electrical equipment installation engineering”.
  - GB3836.13-2013 “Explosive atmospheres- Part 13: Equipment repair, overhaul and reclamation”.
  - GB3836.15-2000 “Electrical apparatus for explosive gas atmospheres- Part 15: Electrical installations in hazardous area (other than mines)”.
  - GB3836.16-2006 “Electrical apparatus for explosive gas atmospheres- Part 16: Inspection and maintenance of electrical installation (other than mines)”.
  - GB3836.18-2010 “Explosive atmospheres-Part 18: Intrinsically safe system”.

### Flameproof

Certificate Number GYJ15.1043X

Ex d IIC T4/T5/T6 Gb

### Special Conditions for Safe Use

The suffix “X” placed after the certificate number indicates that this product is subject to special conditions for safe use, that is:

1. For information on the dimensions of the flameproof joints contact the manufacturer.
2. Avoid of the electrostatic charge built on the surface of non-metallic material of the product.

### Conditions for Safe Use

1. The external earth connection facility should be connected reliably.
2. Electrical data: 30V max, 20mA.
3. Suitable certified cable glands or blanking plugs for unused holes approved by ExTL according to GB3836.1-2010 and GB3836.2-2010 with Ex marking “Ex d IIC Gb” shall be used and correctly installed; after installation, degree of protection of enclosure is at least IP66 according to GB4208-2008.
4. Any maintenance shall be performed only when the warning of “Do not open when energized” is observed.
5. The user shall not change the configuration in order to maintain/ensure the explosion protection performance of this product. Any change may impair safety.
6. For installation, use and maintenance of this product, the end user should observe the instruction manual and the following standards:
  - GB50257-1996 “Code for construction and acceptance of electric device for explosion atmospheres and fire hazard electrical equipment installation engineering”.
  - GB3836.13-2013 “Explosive atmospheres- Part 13: Equipment repair, overhaul and reclamation”.
  - GB3836.15-2000 “Electrical apparatus for explosive gas atmospheres- Part 15: Electrical installations in hazardous area (other than mines)”.
  - GB3836.16-2006 “Electrical apparatus for explosive gas atmospheres- Part 16: Inspection and maintenance of electrical installation (other than mines)”.

**Type n**

Certificate Number GYJ15.1045X

Ex nC IIC T5/T6 Gc (except DVC6215)

Ex nA IIX T4/T5/T6 Gc (only DVC6215)

**Special Conditions for Safe Use**

The suffix “X” placed after the certificate number indicates that this product is subject to special conditions for safe use, that is:

Avoid of the electrostatic charge built on the surface of non-metallic material of the product.

**Conditions for Safe Use**

1. The external earth connection facility should be connected reliably.
2. This product can only be used in the explosive gas area located as zone 2 or safe area.
3. Electrical data: 30V max, 20mA.
4. Suitable certified cable glands or blanking plugs for unused holes approved by ExTL according to GB3836 shall be used and correctly installed; after installation, degree of protection of enclosure is at least IP66 according to GB4208-2008.
5. Any maintenance shall be performed only when the warning of “Do not open when energized” is observed.
6. The user shall not change the configuration in order to maintain/ensure the explosion protection performance of this product. Any change may impair safety.
7. For installation, use and maintenance of this product, the end user should observe the instruction manual and the following standards:
  - GB50257-1996 “Code for construction and acceptance of electric device for explosion atmospheres and fire hazard electrical equipment installation engineering”.
  - GB3836.13-2013 “Explosive atmospheres- Part 13: Equipment repair, overhaul and reclamation”.
  - GB3836.15-2000 “Electrical apparatus for explosive gas atmospheres- Part 15: Electrical installations in hazardous area (other than mines)”.
  - GB3836.16-2006 “Electrical apparatus for explosive gas atmospheres- Part 16: Inspection and maintenance of electrical installation (other than mines)”.

Neither Emerson, Emerson Process Management, nor any of their affiliated entities assumes responsibility for the selection, use or maintenance of any product. Responsibility for proper selection, use, and maintenance of any product remains solely with the purchaser and end user.

Fisher and FIELDVUE are marks owned by one of the companies in the Emerson Process Management business unit of Emerson Electric Co. Emerson Process Management, Emerson, and the Emerson logo are trademarks and service marks of Emerson Electric Co. All other marks are the property of their respective owners.

The contents of this publication are presented for informational purposes only, and while every effort has been made to ensure their accuracy, they are not to be construed as warranties or guarantees, express or implied, regarding the products or services described herein or their use or applicability. All sales are governed by our terms and conditions, which are available upon request. We reserve the right to modify or improve the designs or specifications of such products at any time without notice.

Emerson Process Management  
Marshalltown, Iowa 50158 USA  
Sorocaba, 18087 Brazil  
Chatham, Kent ME4 4QZ UK  
Dubai, United Arab Emirates  
Singapore 128461 Singapore

[www.Fisher.com](http://www.Fisher.com)