## **SIEMENS**

Data sheet 6EP1536-3AA00



SITOP PSU400M/DC/DC/600V/24V/20A

SITOP PSU400M 20 A DC/DC converter input: 600 V DC output: 24 V DC/20 A

Input	
type of the power supply network	DC voltage
supply voltage at AC	
• initial value	startup from 340 V DC; derating necessary at 300 400 V DC and 824 900 V DC
supply voltage	
• at DC	600 600 V
input voltage	
• at DC	300 900 V
overvoltage overload capability	Shutdown at Vin > 900 V DC
input current	
at DC at rated input voltage 600 V	0.85 A
current limitation of inrush current at 25 °C maximum	8 A
I2t value maximum	0.02 A <sup>2</sup> ·s
fuse protection type	yes, cut-off capacity 20 kA; L/R < 2 ms ("+" and "-" input)
Output	
voltage curve at output	Controlled, isolated DC voltage
output voltage at DC rated value	24 V
output voltage	
<ul> <li>at output 1 at DC rated value</li> </ul>	24 V
relative overall tolerance of the voltage	3 %
relative control precision of the output voltage	
<ul> <li>on slow fluctuation of input voltage</li> </ul>	0.3 %
on slow fluctuation of ohm loading	0.3 %
residual ripple	
• maximum	150 mV
typical	30 mV
voltage peak	
• maximum	200 mV
• typical	100 mV
adjustable output voltage	24 28.8 V
product function output voltage adjustable	Yes
type of output voltage setting	via potentiometer; max. 480 W
display version for normal operation	Green LED for 24 V OK, green flashing LED for start delay
type of signal at output	Relay contact (NO contact, rating 60 V DC/ 0.3 A; 30 V DC/1 A) for 24 V OK
behavior of the output voltage when switching on	No overshoot of Vout (soft start)
response delay maximum	0.1 s; 10 s adjustable using switch
voltage increase time of the output voltage	
• maximum	150 ms

output current	
rated value	20 A
rated range	0 20 A; +60 +70 °C: Derating 5.5%/K
supplied active power typical	480 W
short-term overload current	
<ul> <li>on short-circuiting during the start-up typical</li> </ul>	40 A
at short-circuit during operation typical	60 A
duration of overloading capability for excess current	
<ul> <li>on short-circuiting during the start-up</li> </ul>	150 ms
at short-circuit during operation	25 ms
constant overload current	
on short-circuiting during the start-up typical	23 A
product feature	
bridging of equipment	Yes; switchable characteristic
number of parallel-switched equipment resources for increasing the power	2
Efficiency	
efficiency in percent	95 %
power loss [W]	***
at rated output voltage for rated value of the output	25 W
current typical	
Closed-loop control	
relative control precision of the output voltage with rapid fluctuation of the input voltage by +/- 15% typical	1.5 %
relative control precision of the output voltage load step of	1.5 %
resistive load 50/100/50 % typical	
setting time	1 ma
• load step 50 to 100% typical	1 ms
• load step 100 to 50% typical	1 ms
setting time  • maximum	5 ms
Protection and monitoring	3 1113
design of the overvoltage protection	< 33 V
response value current limitation typical	22 A
property of the output short-circuit proof	Yes
design of short-circuit protection	Alternatively, constant current characteristic approx. 22 A or latching
	shutdown
enduring short circuit current RMS value	
• typical	22 A
overcurrent overload capability in normal operation	overload capability 150 % lout rated up to 5 s/min
display version for overload and short circuit	LED yellow for "overload", LED red for "latching shutdown", red LED
Colodia	flashing for "Overtemperature"
Safety	V
galvanic isolation between input and output	Yes
galvanic isolation	Protective extra low output voltage Vout according to EN 60950-1 and EN 50178
operating resource protection class	Class I
protection class IP	IP20
Approvals	
certificate of suitability	
• CE marking	Yes
UL approval	Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259
CSA approval	Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259
• cCSAus, Class 1, Division 2	No
• ATEX	No
certificate of suitability	
• IECEx	No
NEC Class 2	No
ULhazloc approval	No
FM registration	No
type of certification CB-certificate	Yes

certificate of suitability	
<ul> <li>EAC approval</li> </ul>	Yes
C-Tick	No
certificate of suitability shipbuilding approval	Yes
shipbuilding approval	DNV GL
Marine classification association	
<ul> <li>American Bureau of Shipping Europe Ltd. (ABS)</li> </ul>	No
<ul> <li>French marine classification society (BV)</li> </ul>	No
DNV GL	Yes
<ul> <li>Lloyds Register of Shipping (LRS)</li> </ul>	No
<ul> <li>Nippon Kaiji Kyokai (NK)</li> </ul>	No
EMC	
standard	
<ul> <li>for emitted interference</li> </ul>	EN 55022 Class A (emission)
<ul> <li>for mains harmonics limitation</li> </ul>	•
<ul> <li>for interference immunity</li> </ul>	EN 61000-6-2
environmental conditions	
ambient temperature	
<ul> <li>during operation</li> </ul>	-25 +70 °C; with natural convection
<ul> <li>during transport</li> </ul>	-40 +85 °C
<ul> <li>during storage</li> </ul>	-40 +85 °C
environmental category according to IEC 60721	Climate class 3K3, 5 95% no condensation
Mechanics	
Mechanics type of electrical connection	screw-type terminals
	screw-type terminals  DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-
type of electrical connection  • at input	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm
type of electrical connection         • at input         • at output         • for auxiliary contacts  width of the enclosure height of the enclosure depth of the enclosure required spacing         • top	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm 125 mm
type of electrical connection         • at input         • at output         • for auxiliary contacts  width of the enclosure height of the enclosure depth of the enclosure required spacing         • top         • bottom	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm 125 mm 50 mm
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm 125 mm 50 mm 50 mm
type of electrical connection	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm 125 mm 50 mm 0 mm 0 mm
type of electrical connection         • at input         • at output         • for auxiliary contacts  width of the enclosure height of the enclosure depth of the enclosure required spacing         • top         • bottom         • left         • right net weight	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm 125 mm 50 mm 0 mm 0 mm 1.2 kg Yes Snaps onto DIN rail EN 60715 35x7.5/15
type of electrical connection         • at input         • at output         • for auxiliary contacts  width of the enclosure height of the enclosure depth of the enclosure required spacing         • top         • bottom         • left         • right net weight product feature of the enclosure housing can be lined up	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm 125 mm 50 mm 0 mm 0 mm 1.2 kg Yes
type of electrical connection         • at input         • at output         • for auxiliary contacts  width of the enclosure height of the enclosure depth of the enclosure required spacing         • top         • bottom         • left         • right net weight product feature of the enclosure housing can be lined up fastening method	DC input, +, -, PE: 1 screw terminal each for 0.2 6/4 mm² single-core/finely stranded +, -: 2 screw terminals each for 0.2 6/4 mm² single-core/finely stranded Alarm signals: 2 screw terminals for 0.14 1.5 mm² single-core/finely stranded 90 mm 125 mm 125 mm 50 mm 0 mm 0 mm 1.2 kg Yes Snaps onto DIN rail EN 60715 35x7.5/15 Device identification label 20 mm × 7 mm, pale turquoise 3RT1900-

